


Smart Plug User Manual

What's in the Box

Smart Outlet x 1
User Manual x 1

At a Glance



- 1.Socket Panel
2. Power Plug
3. ON/OFF Button
4. Flame Resistant Material

- 01 -

Note: ON/OFF button can be used as restore button, long press can change the flashing speed and will restore your smart socket to factory defaults. Only do this if you are sure you want to erase all your settings.

Parameters

Model Number:
Rated Voltage: AC100-240V
Rated Current: 16 A [Max]
AC Frequency: 50/60Hz
Working Temp.: -20-60°C
WIFI frequency: 2.4 Ghz only
Maximum Total Power Output: 3680W

Install the "Smart Life" APP

1. You may find the "Smart Life" app on Apple App store, Google Play, or scan the QR code below and install it;
2. Enter the register / log in interface, input the email address for getting the verification code to register an account.



- 02 -

The free app "Smart Life" is compatible with mobile devices that support iOS 8.0 above, Android 4.4 above.

Connecting Your Socket with APP

A. Easy Mode [Recommend]

1. Please make sure the mini socket has connected with electricity at the beginning, then open the "Smart Life" APP, tap the "ADD DEVICES" or the "+" at the upper right corner of the page and select "Electrical outlet;"
2. Please wait for the indicator to flash quickly, or long press on/off button of the device for 5 seconds until indicator light quickly flashed, the interface page already stepped into "Add Device" page as the above;
3. Make sure the indicator light is flashing rapidly and confirm it in app;
4. Choose the local WIFI and enter the correct password and confirm;
5. Wait for configuring successfully, then tap "Done".

B. AP Mode

1. Please change to "AP Mode" if connecting failed in "Easy Mode". The AP Mode is at the upper right corner of the "ADD DEVICE" page;
2. Long press on/off button until the indicator light flashes slowly;
3. Make sure the indicator light is flashing slowly and confirm it in App;
4. Choose the local WIFI and enter the correct password and confirm;
5. Tap "Connect Now", choose WIFI hotspot named "SmartLife xxx", then back to "Smart Life" application;
6. Wait for configuring successfully, then tap "Done".

- 03 -

Getting to Know "Smart Life" APP

A.Devices

You can add listed devices by tap the "+" at the top right at this page.

1. Switches

Switches allows you to turn on/off your device anywhere. As long as you have an internet connection you can control the device in your home. Tap to the icon at the upper right of the page, you are able to modify the device name or even create a group (If you have several device), which means you can turn multiple devices on or off at the same time.


2. Timer

Schedule the device "lights" to turn on when you wake up or to automatically turn on when you get home. Turn devices on and off at different times to let people know that someone is home while you are away.

3. Left time

You can set the devices on or off after the specific time as you want with this function.

- 04 -




B. Scenes

With this function, you can create your characteristic scenes as you want.

C. Profile

Profile is the entrance for the users to manage personal information, which mainly show the following information:



- 05 -

Safety Information

The device is recommended for use indoors and in a dry location only, power outlet shall be used within it's published outlet rating on the instructions. Please contact seller for replacement if there is any damage caused by transportation. Please plug in the socket in proper condition and away from children. Please plug in the socket fully while using for safety concern. Please do not disassemble or install the socket, otherwise there may cause product damaged or security risks.

Using Amazon Echo Quick Guide What You'll Need...

- Amazon Alexa APP & Account.
- Smart Life APP & Account (Users need to register your own account, select region as "United State").
- Echo, Echo Dot, Tap or other Amazon voice operated devices.
- Mini Smart Socket.
- Tip: Rename the device after configuring successfully, The name of the device is recommended to use easy pronunciation of the English words.

Set Your Echo Speaker by Alexa APP

1. Sign in with Alexa account & password (If not registered, sign up first); After login, click the menu at the top left, then click "Settings", and choose "Set up a new device";
2. Choose a device (for example, Echo). When the right page appears, long press the small dot on your Echo device until the light turns to yellow. Then click "Continue" on App. (Note: the mobile phone can not open a variety of VPN software at this time);

- 06 -




3. Choose users' WIFI and wait for a few minutes;

4. After an introduction video, click next step, it will turns to "Home" page automatically. Now the Echo is connected to Alexa APP through WIFI successfully.

Enable Our Skill in Alexa APP

1. Choose "Skills" in the options bar, and then search "Smart Life" in the search bar; Select "Smart Life" in the search results, and then click "Enable".
2. Input the user name and password that you had previously registered; When you see the right page, it means the Alexa account is linked with Smart Life account.

- 07 -




Control Smart Socket by Voice

After the previous operation, you can control the socket via Echo.

1. Discovering devices: Firstly, users need to say to Echo: "Echo (or Alexa), Discover my devices." Echo will start to finding the devices which is added in Smart Life APP, it will take about 20 seconds to show the result. Or you may click "Discover devices" in Alexa APP, it will show the devices that found successfully. Note: "Echo" is one of the wake-up name, which can be any of these three names (Settings); Alexa/Echo/Amazon.

2. Support Skill List User can control devices by instructions like below:
Alexa, turn on [fridge socket]
Alexa, turn off [fridge socket]
Attention: The name of the device must be consistent with the addition of Smart Life App.

- 08 -



Warranty

This product carries a one-year warranty from purchase date. Please feel free to let us know what we can do to assist you when you have any product problem.

- 09 -